FREE HOMEOWNER GUIDE

Hardwired smoke detector chirping or beeping? Here's why

Smiley Electric does not take smoke detector jobs, so this page is troubleshooting help, not a service offer. Most chirps clear with the steps below. For panel, wiring, outlet, and other general electrical repair work in the Portland metro, call us.

Why it chirps even after you pull the battery

A hardwired smoke detector that keeps chirping, even after you removed the battery or took it off the ceiling, is almost always at the end of its life or running its low-battery warning off a backup cell you did not know it had. Nearly every hardwired alarm carries a backup battery so it still works in a power outage, and that battery is what keeps the chirp going once the unit is off the wall.

A single chirp every 30 to 60 seconds is a maintenance warning, not a fire alarm. A steady, loud alarm means smoke or carbon monoxide, get everyone out and call 911. The chirp is the unit telling you the backup battery is low, the alarm is dirty, or it has simply aged out. Both phrasings people search, chirping and beeping, point to the same thing.

Find the unit that is actually chirping

In most homes the smoke alarms are interconnected, so when one goes into full alarm they all sound. The low-battery chirp is different: only the failing unit chirps, and in a hallway of identical alarms it can be maddening to locate. Watch for the unit with a blinking red or green LED that flashes in time with the chirp. That is your culprit.

- [ ] Stand under each alarm and wait for the chirp to line up with a blinking light
- [ ] Check smoke and combination smoke-CO units in bedrooms, hallways, and near the kitchen
- [ ] A combination CO alarm can also chirp when its CO sensor has expired, which is a separate end-of-life clock

Steps that usually stop it

Work through these in order. Most chirps are solved by the second or third step. Do this with the alarm you identified, not every unit in the house.

- [ ] Replace the backup battery, even though the unit is hardwired, and seat it fully until the drawer clicks
- [ ] Press and hold the test button for several seconds to clear the residual charge and any latched warning
- [ ] Read the manufacture date printed on the back of the alarm; smoke detectors expire 10 years from that date and must be replaced, not repaired

- [ ] Blow out dust with canned air, since dust and Portland humidity both trigger nuisance chirps
- [ ] If the whole interconnected string is acting up, replace the oldest units, because a single failing alarm can chirp the others
- [ ] Flip the breaker for that circuit off and back on to reset the alarm after a power blip

When it is an electrician's problem

Most chirps are a battery or an expired alarm. A few point at the wiring behind the unit. If a hardwired alarm chirps or false-alarms right after a power flicker, if the green power light is dark, or if the circuit feeding the alarms trips, the issue is on the electrical side. Interconnected alarms share a traveler wire, and a loose connection in that run can make the whole string misbehave. At that point it is a job for a licensed electrician rather than another battery.

- [ ] The green AC power light on the alarm is off
- [ ] Alarms false-trigger every time the power blips
- [ ] The breaker or AFCI on the smoke-alarm circuit trips
- [ ] Alarms are older than 10 years and the whole system is due

Frequently asked questions

Why does my hardwired smoke detector chirp with no battery in it?

Hardwired alarms carry a backup battery so they keep working during an outage, and that backup is usually what chirps. If you pulled the removable battery and it still chirps, the unit may have a sealed backup cell, latched residual charge, or has reached its 10-year end of life. Replace the backup battery, hold the test button to clear it, and check the manufacture date on the back.

How do I find which smoke detector is chirping?

Only the failing unit chirps, and it usually blinks a red or green LED in time with the chirp. Stand under each alarm until the light and the chirp line up. In an interconnected system the alarms all sound together only during a real alarm, so the lone chirp is coming from one specific unit.

How long do hardwired smoke detectors last?

About 10 years from the manufacture date printed on the back of the unit, not from when you installed it. After that the sensor degrades and the alarm should be replaced rather than repaired. If yours is near or past that age and chirping, replacement is the fix.

Should I call an electrician for a chirping smoke detector?

Not usually, since most chirps are a low backup battery or an expired alarm you can replace yourself. Call a licensed electrician if the green AC power light is off, the alarms false-trigger after a power flicker, or the circuit feeding them trips. Those point to a wiring or interconnect problem rather than the alarm itself.

Sources

1. Smoke Alarms, U.S. Fire Administration. https://www.usfa.fema.gov/prevention/home-fires/prepare-for-fire/smoke-alarms/

2. Learn More About Smoke Alarms, National Fire Protection Association (NFPA). https://www.nfpa.org/education-and-research/home-fire-safety/smoke-alarms
3. Smoke Alarms, Carbon Monoxide Alarms and Fire Escape Planning, Electrical Safety Foundation International (ESFI). https://www.esfi.org/smoke-alarms-carbon-monoxide-alarms-and-fire-escape-planning/

> **Need a licensed electrician in the Portland area?**
> Call Smiley Electric at (503) 484-7556 (Mon–Sat, 7am–5pm) or visit smileyelectric.net/contact. For sparks, smoke, a burning smell or a hot panel, turn off the power if it is safe and call right away.

Reviewed by Joshua Smiley, owner & master electrician, Smiley Electric. Last reviewed November 13, 2026. Online version: smileyelectric.net/help/hardwired-smoke-detector-chirping/. General information, not a substitute for an on-site inspection.
Cite this page: Smiley Electric. “Hardwired smoke detector chirping or beeping? Here's why.” smileyelectric.net/help/hardwired-smoke-detector-chirping/. Last reviewed November 13, 2026. You are welcome to quote, print or share this page with credit to Smiley Electric and a link to smileyelectric.net/help/hardwired-smoke-detector-chirping/.